

## Selected Data for JFETS

by Kenneth A. Kuhn  
rev. Sept. 20, 2008

Here are some selected data for common n-channel JFETs.

<b>Type</b>	<b>I<sub>DSS</sub> (mA)</b>		<b>V<sub>P</sub> (Volts)</b>		<b>g<sub>mo</sub> (mS)</b>
	<b>min</b>	<b>max</b>	<b>min</b>	<b>max</b>	
2N3819	2	20	-0.5	-7.5	8
2N3821	0.5	2.5	-0.5	-2	2.5
2N3822	2	10	-1	-4	5
2N3823	4	20	-1	-7.5	8
2N3970	50	150	-4	-10	30
2N3971	25	75	-2	-5	30
2N3972	5	30	-0.5	-3	20
J310	24	60	-2	-6.5	24
MPF102	2	20	-0.5	-8	5
MPF108	1.5	24	-0.5	-8	6
MPF109	0.5	24	-0.2	-8	6